



Complete Fixture consists of Reflector Trim & Frame-In Kit. Select each separately.

Conversion Kit	Compatible Incandescent Frame-in Kits	Compatible Reflector Trims — See Individual Reflector Trim Specification Sheets			
1920LV	<b>1002P1</b> <b>1000IC</b> <b>1003R</b> <b>1000AICM</b>	Adjustable			
		Step Baffle	Aperture Cone	Pinhole	Elbow
		<b>1055LV</b> <b>1055WHLV</b>	<b>1063LV</b> <b>1064WDLV</b> <b>1064LV</b> <b>1064WDPLV</b>	<b>1052LV</b>	<b>1062LV</b>

### Features

- Transformer Housing:** 0.036" (#20 ga.) steel. Matte black finish.
- Transformer:** Magnetic, 120V primary, nominal 12V secondary.
- Socket:** Field replacable. Two-pin socket, pre-wired with #18 SF1 leads.
- Socket Adaptor:** Medium base; nickel-plated screw shell. Pre-wired with #18 ga. SF1 leads. Screws into previously installed Lytecaster® incandescent Frame-in Kits to energize conversion kit.
- Socket Housing:** 0.036" (#20 ga.) galvanized steel.

### Dimming Information

Dimming Controls: use only dimmers specifically designed for use with magnetic transformers, like Lightolier Onset® or Sunrise® series LV or VA dimmers, or any Lightolier Controls dimming system. Low voltage fixtures may produce audible sound when used with dimmers, which may be objectionable in acoustically critical areas.

### Options & Accessories

**MR16 Replacement Socket:** 1975A

### Labels

UL (Suitable for Damp Locations), I.B.E.W.

Lytecaster® is a registered trademark of Lightolier.

Job Information	Type:
<b>Job Name:</b>	
<b>Cat. No.:</b>	
<b>Lamp(s):</b>	
<b>Notes:</b>	

631 Airport Road, Fall River, MA 02720 • (508) 679-8131 • Fax (508) 674-4710  
 We reserve the right to change details of design, materials and finish.  
 www.lightolier.com © 2008 Philips Group • D1108