


FRAME-IN KIT



REFLECTOR TRIM

Complete Fixture consists of Reflector Trim & Frame-In Kit. Select each separately.

| 2000LVR | Open Downlight | | | | | Adjustable | | Enclosed Diffuser |
|---------|----------------|------------|---------|------|---------|-------------|---------|----------------------|
| | Aperture Cone | Satin Cone | Baffles | Slot | Pinhole | Mini Swivel | Eyeball | |
| | 2012 | 2008 | 2005 | 2006 | 2011 | 2025WH | 2022LV | 2026WH |
| | 2012NM | 2008NM | 2005WH | | | | | 2090LV |
| | 2013BKNM | 2010 | 2005BNM | | | | | |
| | 2013CD | 2010NM | 2005NM | | | | | |
| | 2013CDNM | | | | | | | |
| | 2013NM | | | | | | | |
| | 2013BK | | | | | | | |
| | 2013WH | | | | | | | |
| | 2013 | | | | | | | |
| | 2013WD | | | | | | | |
| | 2013WDP | | | | | | | |

Features

- Junction Box:** 2" x 2" x 2 5/8"; .036" (#20 ga.) galvanized steel. UL listed for 90° C supply wire. Integral cable clamps permit attachment of nonmetallic Romex® or armored cable without need of additional connectors.
- Socket Housing:** Aluminum, with lamp adjustment assembly allows vertical and horizontal adjustment, (see reflector trim specification sheet for specific adjustment).
- Socket:** Field replaceable. Two pin socket, pre-wired with #18SF1 leads to junction box.
- Transformer:** Outboard mounted, magnetic, 120V. primary, nominal 12V. secondary. Removable from below.
- Thermal Protector:** Meets NEC and UL requirements. Insulation must be kept 3" away from fixture sides and wiring compartments and must not be placed above fixture in a manner which will entrap heat.
- Mounting Ring:** .048 (#18 ga.) galvanized steel. Accommodates existing ceilings up to 2" thick. Attaches securely to any type of ceiling material without tools using (3) mounting straps provided. Push-in/twist out clips hold reflector flush to ceiling. Includes adhesive backed aperture template.
- Nail Clips:** Secures junction box and plate to ceiling.

Dimming

Dimming Controls: Use only dimmers specifically designed for use with transformers, like Lightolier Onset®, Sunrise® series LV or VA dimmers, or any Lightolier Controls dimming system. Low voltage fixtures may produce audible sound when used with dimmers, which may be objectionable in acoustically critical areas.

Options & Accessories

- MR16 Socket Replacement:** 1975B
277V Remote Step Down Transformer: 7997 - 277V down to 120V
 300W max. load.

Socket for General Electric Turn and lock (TAL) MR16 Lamp: 1975TAL

Labels

UL (Suitable for Damp Locations), I.B.E.W.

Romex® is a registered trademark of General Cable Industries Inc.

| Job Information | Type: |
|------------------|-------|
| Job Name: | |
| Cat. No.: | |
| Lamp(s): | |
| Notes: | |

631 Airport Road, Fall River, MA 02720 • (508) 679-8131 • Fax (508) 674-4710
 We reserve the right to change details of design, materials and finish.
 www.lightolier.com © 2011 Philips Group • K0811